

## Hikvision DS-K1T341AM Face Recognition Terminal Setting up the DS-K1T341AM with the Bosch Solution 6000 panel

### Required Parts:

- Hikvision DS-K1T341AM(F) 4.3" Face Recognition Terminal
- Bosch Solution 6000
- CM796B Wiegand to DF RS485 LAN Interface Module

### Step 1: On DS-K1T341AM(F) terminal

- Activate Device at the Start Up Screen (Follow when prompted)
- Keep following prompt to add Admin User

### Step 2:

- Hold Finger on screen until Swipe Finger Symbol appears, then Swipe Left
- Log into Unit with Username and Pass Code
- Go to User Icon and Press +
- Edit Name
- Add Card (**this is required**) then Press + You can use a generic number here, ie made up number OR use a MiFare Card.
- Press Tick to Save
- Add Face and/or Fingerprint Press + to add then (Tick) to Save

### Step 3:

- Go to Comm Icon
- Go to Wiegand - Tap to On and Change from Input to Output, leave as 26 Bit then Press <

### Step 4:

- Exit Programme

### Step 5: On Solution 6000

- Make Sure that you have set up Door Control on the Panel Refer Pg 9 on Bosch Solution 6000 Quick Reference Guide.

### Step 6:

- Menu 1-2-0      ADD TOKEN      Choose Reader **Wi# Keypad # Name**
- Select User

**Step 7:** Present Face to Face Terminal, wait for the Read on the Solution 6000.

**Step 8:** For more faces repeat Step 5.

**Step 9:** Press and Hold the Menu Key to Exit.

## Wiring Diagram:

