

# Ness Radio Keypad

Product Code: 100-001



## Dimensions:

90W x 135H x 27D mm (with lid closed)

## Compatibility:

- 100-200 Ness Radio Interface.  
(Ness D8, D16, D24)
- 100-187 Ness 1ch Standalone Receiver.
- 100-666 Ness MCR receiver.

## Keypad Functions:

- Arming/Disarming by User ID
- Home mode
- Panic alarm
- AUX 1 (to D8 & D16 Panels)
- AUX 2 (to MCR Receiver)

---

<b>Audible indicator:</b>	Onboard beeper for feedback: keypress, valid command, error.
<b>Visual indicators:</b>	<u>VALID LED</u> : indicates program modes, valid signal. <u>LOW BATTERY LED</u> : indicates RKP low battery, option enabled (program mode).
<b>Battery:</b>	9V Lithium ( <i>Ultralife U9VL</i> )
<b>Quiescent current draw:</b>	11µA
<b>Radio transmitter:</b>	SAWR stabilised
<b>Radio frequency:</b>	303.875MHz
<b>Transmit power:</b>	100µW PEP

---

## National Fire & Security Ltd

1/44 Greenpark Road, Penrose, Auckland | 09 580 1576 | sales@nfs.co.nz