


REMOTE ORDERING OPTIONS

Art ID:
SGT090



SPECIFICATIONS
 >>>SGT
 Frequency - 433Mhz
 Buttons - 4
 Battery - LR27A

COMPATIBLE WITH



RECEIVER COMPATIBILITY

- Suits Models:
ECA Max / DCP-240, Big Foot 2200, SG-200, SR-5000, XR-900, Ultra, SG-560SL-400, SL-450, 81CR, 82CR, 84CR, ACR-6

Remote Programming Steps

Program Existing Remote to New Remote

SGT090

- Take an existing working remote, and stand about 2m away from your receiver (garage door motor).
- Using your existing remote, press and hold both the buttons (III) and (I) simultaneously for 5 seconds. The LED light on your receiver (garage door motor) will turn on.
- Using your new remote control, press any hold any button for 5 seconds, until the LED light on the receiver (garage door motor) turns off.

Program Remote to Receiver

SGT090

- Remove the “Clear” jumper on the receiver (garage door motor). The LED light will turn on.
- Using your new remote control, press any hold any button for 5 seconds, until the LED light on the receiver (garage door motor) turns off. Your new remote has been accepted.
- Place the “Clear” jumper back on.

Deleting All Remotes from Receiver

SGT090

- Disconnect the power supply and remove the “Clear” Jumper on the receiver (garage door motor).
- Wait for 3 seconds and reconnect the power supply. The LED on the receiver (garage door motor) will turn on.
- Before the LED light turns off, put back the “Clear” jumper
- The LED will flash twice to indicate that all remotes have been erased.

Whilst every effort has been made to ensure the accuracy of the information supplied herein, we assume no liability for any errors or omissions. Information contained in this document is subject to change without prior notice.