



## AKG C214 Large-Diaphragm Condenser Microphone

- Cardioid Pattern
- 1-Inch Capsule
- Switchable 20 dB Pad & Low-Cut Filter
- 143 dB Dynamic Range
- Integrated Capsule Suspension
- Double-Mesh Grille for RF Immunity
- Gold-Plated XLR Connector
- Shockmount, Windscreen, Carrying Case
- Built in Austria

### What's in the Box

AKG C214 Large-Diaphragm Condenser Microphone  
H 85 Universal Shock Mount  
W214 Foam Windscreen  
Metal Carrying Case

### Specs

## AKG C214 Specs

#### Microphone

Diaphragm	1.0" / 25.40 mm
Polar Pattern	Cardioid
Pad	-20 dB
High-Pass Filter	160 Hz

#### Performance

Frequency Range	20 Hz to 20 kHz
Impedance	200 Ohms
Load Impedance	1000 Ohms

Sensitivity	20 mV/Pa
Dynamic Range	143 dB A-Weighted
Signal-to-Noise Ratio	81 dB A-Weighted
Equivalent Noise Level	13 dB A-Weighted

### Connectivity

Output Connectors	1 x XLR 3-Pin
-------------------	---------------

### Power

Operating Voltage	9 to 52 V
Operating Current Consumption	2.0 $\mu$ A

### Physical

Operating Temperature	14 to 140°F / -10 to 60°C
Dimensions	$\varnothing$ : 2.2 x L: 6.3" / $\varnothing$ : 55.88 x L: 160 mm
Weight	9.88 oz / 280 g