



MINI 10 YEAR INTERCONNECTED

# SMOKE ALARM

MODEL NUMBER:

## AJ-770SI4

The Watchman Mini 10 Year Wireless Interconnected Smoke Alarm can connect up to 22 alarms which provides greater protection and early detection throughout the home. When one alarm activates, all other connected alarms will activate.

The alarm contains cutting-edge, dual-sensor technology. Dual-sensor allows the alarm to make more accurate readings inside the sensing chamber, and along with the additional insect mesh, helps reduce the potential of nuisance alarms caused from environmental factors. The alarm also contains a quick and automated pairing process and connects with the Watchman Wall Controller for simpler functionality. Smoke alarms are designed to be installed in bedrooms, dining rooms, living areas and hallways.



### PRODUCT & TECHNICAL SPECIFICATIONS:

|                            |                  |
|----------------------------|------------------|
| Product Size:              | 78mm x 57mm      |
| Gross Weight:              | 0.11kg           |
| Sound:                     | 85dB at 3 meters |
| Humidity:                  | 95% RH           |
| Standby Current:           | < 10uA           |
| Alarm Current:             | < 60mA           |
| Optimal Temperature Range: | -100 - + 500     |
| RF Frequency:              | 433MHz           |

### FEATURES:

- » Built-in 10 Year 3v lithium battery
- » Automated RF pairing process
- » Dual-Sensor technology
- » 9 minute hush
- » Wall Controller available
- » Easy to install
- » 10 year warranty
- » EN14604:2005 certified
- » NZ Building Code, NZS4514:2021 and RTA compliant



SIMPLE AUTOMATED  
INTERCONNECTING



DUAL SENSOR  
TECHNOLOGY



WALL CONTROLLER  
AVAILABLE



2 LAYERS OF  
INSECT MESH



ALL PACKAGING IS  
100% RECYCLABLE



WIRELESS

# WALL CONTROLLER

MODEL NUMBER:

## AJ-R1063

The Watchman Wall Controller is a portable wireless remote controller which can connect to the Watchman AJ-770SI4 and AJ-770T4 smoke and heat alarms. The Wall Controller functions provide a more convenient way to control your interconnected alarm system and will help if your alarms are not very accessible.

The AJ-R1063 is compatible with older Watchman models; AJ-760SI and AJ-965TU4.



### PRODUCT & TECHNICAL SPECIFICATIONS:

|                 |                       |
|-----------------|-----------------------|
| Product Size:   | 75mm x 16mm           |
| Gross Weight:   | 0.04kg                |
| Certifications: | UKCA-RED, CD-RED, EMC |



SIMPLE AUTOMATED  
INTERCONNECTING

ALL PACKAGING IS  
100% RECYCLABLE



### FEATURES:

- » **TEST:** Allows you to test any alarm in a network for 10-15 seconds
- » **LOCATE:** Helps to quickly identify the originally activated alarm. This feature will silence all alarms in the network, apart from the originally activated alarm - which will continue to sound
- » **HUSH:** Silence all alarms within the network. As a safety measure, the originally activated alarm contains a memory function and will emit 3 beeps per minute until silenced from the alarm or pressing the 'TEST' button on the controller
- » RF technology and connects with Watchman wireless alarms
- » DC 3V (2 x AAA batteries - Replaceable)
- » Easy to install
- » Wall bracket for convenient placement